


Abbildung ähnlich /  
Illustration similar

106,2kVA ENDRESS POWER Line -generator with electric start

## TEKNISET TIEDOT

|                                               |                      |
|-----------------------------------------------|----------------------|
| <b>Tuotekoodi</b>                             | E333255              |
| <b>Model</b>                                  | 4-cylinder 4-stroke  |
| <b>Measurements L x W x H mm</b>              | 2414 x 1087 x 1683   |
| <b>Weight (kg) ~</b>                          | 1500kg               |
| <b>Running time at 75% load (h)</b>           | 12,3h                |
| <b>Cooling system</b>                         | water cooled         |
| <b>Revolutions per minute (rpm) / control</b> | 1500/ Electronic     |
| <b>Fuel cons. at 75% PRP [L/h]</b>            | 17l                  |
| <b>Volume</b>                                 | 4400 cm <sup>3</sup> |
| <b>Start-up system / battery</b>              | Electric starter 12V |

|                                             |                        |
|---------------------------------------------|------------------------|
| <b>Max. Output [LTP] kVA / kW 3 ~</b>       | 116,0 / 92,8<br>kVA/kW |
| <b>Engine output (LTP) kW</b>               | 95,5kW                 |
| <b>Nominal voltage V</b>                    | 400V 3~ / 230V 1~      |
| <b>Nominal current / Cos theta</b>          | 153,2A 3~ / 0,8        |
| <b>Continuous power [PRP] kVA / kW 3 ~</b>  | 106,2 / 84,9<br>kVA/kW |
| <b>Fuel tank capacity [l]</b>               | Diesel / 209           |
| <b>Sound pressure level LPA (7m) db (A)</b> | 71 db(A)               |
| <b>Sound pressure level LPA db(A)</b>       | 96 db(A)               |
| <b>Frequency / regulation</b>               | 50 Hz / electric       |