



14,5/13,2kVA ENDRESS Power Line MS/AS -generator

## TEKNISET TIEDOT

|                                    |                     |
|------------------------------------|---------------------|
| <b>Tuotekoodi</b>                  | E331221             |
| <b>Model</b>                       | Yanmar 3TNV88-BGPGE |
| <b>Measurements L x W x H mm</b>   | 1805 x 884 x 1261   |
| <b>Weight (kg) ~</b>               | 580                 |
| <b>Alternator type</b>             | synkroni            |
| <b>Sockets</b>                     | CEE 400V / 32A 1x   |
| <b>Displacement [cm3]</b>          | 1642                |
| <b>Jatkuva teho (PRP) kVA/kW</b>   | 13.2/10.5           |
| <b>Fuel cons. at 75% PRP [L/h]</b> | 2.84                |
| <b>Start-up system</b>             | Sähkökäynnistin     |

|                                        |           |
|----------------------------------------|-----------|
| <b>No. of motor cylinders and type</b> | 3L        |
| <b>Nominal voltage V</b>               | 400/230   |
| <b>Nimellisvirta 3~ (PRP) A</b>        | 19.9      |
| <b>Fuel</b>                            | Diesel    |
| <b>Main circuit breaker [Pole]</b>     | 3         |
| <b>Max. Output [LTP] [kVA/kw]</b>      | 14,5/11,6 |
| <b>Fuel tank capacity [l]</b>          | 68        |
| <b>Taajuus Hz</b>                      | 50        |
| <b>Tehokerroin (Cos theta)</b>         | 0.8       |
| <b>Sound pressure level LPA db(A)</b>  | 94        |