

6,6/6,0 kVA ENDRESS DUPLEXplus Line -generator



TEKNISET TIEDOT

Tuotekoodi	E113557I
Model	Honda GX 390
Measurements L x W x H mm	780 x 550 x 595 mm
Weight (kg) ~	113kg
Running time at 75% load (h)	15,5h
Shockproof sockets	2 x 230 V/16 A 1 x CEE 400 V/16 A
Continuous power	6,0 / 4,8 kVA/kW
Kompressorit ja pumput enint.	2400 W
Fuel cons. at 75% PRP [L/h]	2,1l
Volume	389 cm ³
Start-up system	Akkuavusteinen sähkökäynnistin
Possible applications	400 V
Max. Ulostulo [LTP] kVA/kW	6,6 / 5,3 kVA/kW
No. of motor cylinders and type	1-cylinder 4 -stroke OHV
Nominal voltage V	400 V

Nimellisvirta A	8,7 A
Fuel	Petrol
Puutarhatyökalut (asti)	3200 W
Protection class	54 IP
Fuel tank capacity [l]	33l
Taajuus Hz	50 Hz
Teho 3000 r/min nopeudella kW	6,4 kW
Tehokerroin (Cos theta)	0,8 cos φ
Alternator model	Duplex
Sound pressure level LPA (7m) db (A)	60 db(A)
Sound pressure level LPA db(A)	97 db(A)
Electric tools up to	4700 W
Electric devices up to	4800 W
Welding tools up to	3,25 mm dia.

