



6,6/6,0 kVA ENDRESS DUPLEXplus Line -generator

TEKNISET TIEDOT

Tuotekoodi	E113557I	Nimellisvirta A	8,7 A
Model	Honda GX 390	Fuel	Petrol
Measurements L x W x H mm	780 x 550 x 595 mm	Puutarhatyökalut (asti)	3200 W
Weight (kg) ~	113kg	Protection class	54 IP
Running time at 75% load (h)	15,5h	Fuel tank capacity [l]	33l
Shockproof sockets	2 x 230 V/16 A 1 x CEE 400 V/16 A	Taajuus Hz	50 Hz
Continuous power	6,0 / 4,8 kVA/kW	Teho 3000 r/min nopeudella kW	6,4 kW
Kompressorit ja pumput enint.	2400 W	Tehokerroin (Cos theta)	0,8 cos φ
Fuel cons. at 75% PRP [L/h]	2,1l	Alternator model	Duplex
Volume	389 cm ³	Sound pressure level LPA (7m) db (A)	60 db(A)
Start-up system	Akkuavusteinen sähkökäynnistin	Sound pressure level LPA db(A)	97 db(A)
Possible applications	400 V	Electric tools up to	4700 W
Max. Ulostulo [LTP] kVA/kW	6,6 / 5,3 kVA/kW	Electric devices up to	4800 W
No. of motor cylinders and type	1-cylinder 4 -stroke OHV	Welding tools up to	3,25 mm dia.
Nominal voltage V	400 V		