



Valmu lighting transformer is the central unit of the 48VAC lighting system. A total of 75 lights can be connected to a safe low voltage network in one 1500 VA transformer. The lights are divided into three circuits, each with its own switch, quick fuse and indicator light. The transformer has a main switch. Thanks to the indicator lights, it is easy to see from the transformer whether power is coming in to the transformer and to all of the circuits. Lightweight and efficient Valmu transformer can be hung on the wall from the suspension loops. The connection is fast thanks to the spring connectors. Strain relief is done on the transformer bar. Valmu is made in Finland.

TEKNISET TIEDOT

Tuotekoodi	20105007 (20105006)	Weight	15,5 kg
Power	2000 VA	Supply	230 VAC
No. of lighting circuits	3 kpl	Output voltage	48 VAC
Lights in total	75 kpl (3 x 25 kpl)	Warranty (years)	2 år

KUVAT

